



# MODEL CI-50

## 50 AMPS CURRENT INTERRUPTER

### FEATURES:

- Interrupt AC or DC
- ON / OFF 0.1 sec to 99.9 sec
- Cable With Locking Connector
- LEDs show OPEN / CLOSED
- View Program shows cycle settings
- Battery operated (AA batteries)
- Easy to Operate / Program
- Cable Storage In Case
- Tan Colored Lockable Case Blends Into Surroundings

**AVAILABLE  
FROM STOCK**



*Distributed by:*



**BEIJING ROYAL TRADE CO.LTD**  
(FROM 2014 TO 2022)

**Info@tinker-rasor.com.cn | tinker-rasor.com.cn**

Tinker & Rasor quality is found in our products, our people and our customer service.

# TINKER & RASOR

## PRODUCT DATA SHEET | MODEL CL-50 CURRENT INTERRUPTER

### FEATURES:

- Interrupt AC or DC side of the rectifier
- No polarity concerns
- 0.1s- 99.9s programming (0.1 sec increments)
- Highly Accurate Internal Clock
- LEDs show OPEN and CLOSED condition during operation
- Battery operated (AA)
- Battery life up to 100 hours
- Low battery indication

### CONSTRUCTION:

- Solid state circuitry, no mercury relays
- Hard plastic resin case with strong lid latches Lock case with lid locked or able to open
- Low profile tan color
- Case includes internal storage area
- Easy to read, high contrast panel

### APPLICATIONS:

- Interruption of CP rectifiers
- DCVG
- Pipe to Soil Potential
- Instant OFF
- Other potential readings

### SPECIFICATIONS:

- 50 Amp max, AC or DC
- 120 Volt max, AC or DC
- ( 4 ) "AA" Batteries
- Starts in Open condition
- -19°C to 60°C (-2°F to 140°F)

### DIMENSIONS:

5.75" x 12.25" x 10", 5 lbs  
(146mm x 311mm x 254mm, 2.27 kg)

### SHIPPING DIMENSIONS:

14" x 12" x 6", 6 lbs

**DELIVERY:** Immediately from STOCK  
F.O.B. New Braunfels, TX USA

**SERVICE:** 24-hour Turn-Around

**TERMS:** Net 30 Days, on approval of credit

**WARRANTY:** 90 Days, parts and labor



Easy to use and operate, the CI-50 can be programmed in seconds and interrupting immediately.



The small panel size of the CI-50 allows for a large amount of storage room inside the case.

The case can also be locked.



The CI-50 uses AA batteries. Easy to find and easy to replace.

The AA batteries in the CI-50 will keep it operating for more than 80 hours.



The CI-50 Interrupter comes with the cable included. The single, locking connector leads to a pair of booted clamps. Cable length is 6' (1.8m) (p/n: 026-085)

**AVAILABLE FROM STOCK**

[tinker-rasor.com.cn](http://tinker-rasor.com.cn)