



MODEL TriStar

50AMPS GPS CURRENT INTERRUPTER

FEATUR

- 50 Amps (6,000 Watts)
- Gps Timing for Sync With Others 0.005s to 999.999s Cycle Range
- Solid State Switching
- Cable Storage in Case
- Operates from Ac Power
- Removable Magnetic Antenna
- 10 Program Memory
- Non Polarity Connections

**AVAILABLE
FROM STOCK**



All T&R Current Interrupters come complete in one unit with all necessary accessories included, and storage for cables inside the case.

There is nothing else to buy or needed to interrupt a rectifier.

Distributed by:



BEIJING ROYAL TRADE CO.LTD

(FROM 2014 TO 2022)

Info@tinker-rasor.com.cn | tinker-rasor.com.cn

Tinker & Rasor quality is found in our products, our people and our customer service.

TINKER & RASOR

PRODUCT DATA SHEET | MODEL TRISTAR 50 AMP GPS INTERRUPTER

FEATURES:

- Interrupt up to 50 Amp@ 120 Volt (6,000 watt Max.)
- GPS Timing for Synchronization with other units
- Cycle between 000.005s and 999.999s
- 115v - 230v Auto sensing AC power supply
- Removable magnetic mount GPS Antenna
- Manual Sync feature
- 10 Program memory
- Transfer program information to multiple units
- Internal cable storage
- Secure with lid open or closed
- All connections made from outside of case
- Keypad operation with large LCD screen

CONSTRUCTION:

- Rugged carrying case design for rough field use.
- Sealed against dust and water (not immersion)
- Solid state circuitry, no mercury relays
- Reinforced locking rings, lock with lid open or closed
- Internal storage of cables

APPLICATIONS:

- CIPS
- DCVG
- CP Monitoring
- Pipe - to - Soil Potentials
- Interrupt Ground beds

SPECIFICATIONS:

50 Amp max, AC or DC
120 Volt max, AC or DC
Display: 0°C to 50°C (32°F to 122°F) Powered from 115v or 230v (60/50 cycle) AC

DIMENSIONS:

10.62" X 9.68" X 6.87", 15 lbs
(269.79mm x 245.87mm x 174.50mm, 6 kg)

SHIPPING DIMENSIONS:

11" x 7.5" x 10.5", 16 lbs
(279.40mm x 190.50mm x 266.70mm, 7 kg)

DELIVERY: Immediately from STOCK
F.O.B. New Braunfels, TX USA

SERVICE: 24-hour Turn-Around

TERMS: Net 30 Days, on approval of credit

WARRANTY: 90 Days, parts and labor



MODEL TRISTAR GPS CURRENT INTERRUPTER

AVAILABLE FROM STOCK

tinker-rasor.com.cn